- 1. Turn off your internet
- 2. Power off AutoTiss One
- 3. DO NOT plug-in AutoTiss One
- 4. Double click install_driver.exe to install driver
- 5. Plug-in AutoTiss One to your computer



- 6. Go to search icon at the lower left corner
- 7. Type in "device manager" to launch the driver update



8. Right mouse button click on "Prolific USB-to-Serial Comm Port (COM)" and select "Update Driver Software..."

		×
←	Update Driver Software - Prolific USB-to-Serial Comm Port (COM3)	
	How do you want to search for driver software?	
	→ Search automatically for updated driver software Windows will search your computer and the Internet for the latest driver software for your device, unless you've disabled this feature in your device installation settings.	
	→ Browse my computer for driver software Locate and install driver software manually.	
		Cancel

		×
←	Update Driver Software - Prolific USB-to-Serial Comm Port (COM3)	
	Browse for driver software on your computer	
	Search for driver software in this location:	
	C:\Users\Test\Documents	
	☑ Include subfolders	
	ightarrow Let me pick from a list of device drivers on my computer	
	This list will show installed driver software compatible with the device, and all driver software in the same category as the device.	
	Next Car	ncel

			×
÷	<u> </u> Updat	te Driver Software - I-756x (COM3)	
	Select t	the device driver you want to install for this hardware.	
		Select the manufacturer and model of your hardware device and then click Next. If you have a disk that contains the driver you want to install, click Have Disk.	
	Show	compatible hardware	
	Model	ix fic USB-to-Serial Comm Port	
	📺 This <u>Tell</u>	s driver has an Authenticode(tm) signature. Have Disk me why driver signing is important]
		Next Cancel	

		×
~	Update Driver Software - I-756x (COM3)	
	Windows has successfully updated your driver software	
	Windows has finished installing the driver software for this device:	
	I-756x	
		Close



9. COM port number might be different on your computer. Open the setting.txt file and change accordingly.

com 3	
dirX 0	
dirY 0	
homeX 0	
homeY 0	
homeDirX 0	
homeDirY 0	
ppmX 51200	
ppmY 51200	
mprX 2	
mprY 2	
homeOffsetX 2100000	
homeOffsetY 700000	
limitX 80	
limitY 25	
donorX 64	
donorY 12	